


2.4G Wireless Controlled Devices

Need a Control Center (gateway) connecting to App firstly.



YE-880(IOT)-D Door/Window Sensor

When door/window or closet's door is opened, the sensor will send the feedback to the smart-phone and alarm raises at the same time.



Power supply: AAA batteries x 2pcs (1.5V) or by USB port DC5V 0.5A

Remote control distance: within 15M

Instruction for installing:

1. Make sure the Control Center (gateway) is already connected to App.
Scan private S/N code on each 2.4G device for adding under the Control Center.
2. Use a pin to insert the "Reset" hole located at the side of side of the device for switching, and release around 6 seconds later. The indicated led will be fast flashing. Then add the device to App for controlling.
3. Fix the Sensor body on the door frame and Sensor magnet on the active edge. Keep the distance between these two parts no be excess 10mm. Align the "Mark" at the same level.
(Double sided tape can be used for fixing on door.)
4. Forced press "Cap buckle" to open the battery box for replacing a new battery.
(Life of battery can be displayed in App once trigger occurred within 30 seconds.)
(When power supply is from USB port, the battery supplying will be auto-outage.)

